ESU1808: Readme

driver, control panel, firmware for Mac OS X
version: *2.0.2* | date: *2010-05-19* | filename: *ESU1808-Mac-v2_0_2.dmg* | product: *ESU1808*

ESU1808 v2.0.2 for Mac OS X with firmware v1.0.8

This driver update is required if you are using ESU1808 under Mac OS X 10.6 (Snow Leopard) and also strongly recommended for all older versions of Mac OS X. Please note that using this driver requires you to upgrade the firmware of your ESU1808. This firmware update only has to be done once on every unit. This description is devided into three sections:

1. uninstallation of previous driver
2. installation of new driver
3. firmware update (required)

If you have not installed ESU1808 on your Mac yet, you can skip the first of the three sections. The firmware update is always required once.

1. uninstallation of previous driver

If you have already installed ESU1808, it is required to remove the previous driver. To do that, launch the *ESU1808 driver remover* from the downloaded disk image file:

A new dialog will appear that looks like this:



Click *Uninstall*. After a few seconds, the window will appear like this:

Copyright © 1998-2026 ESI Audiotechnik GmbH - All rights reserved.

Click *Exit* and then reboot they system (required).

2. installation of new driver

To install the new driver, you need to launch the installer package from the downloaded disk image:



The standard installer dialogs from Mac OS X will appear. Please follow the process on screen. More details about this can also be found in the printed ESU1808 manual.

Copyright © 1998-2026 ESI Audiotechnik GmbH - All rights reserved.



Once the installation is complete, confirm it with the *Restart* button in the last dialog. Your system will reboot.

3. firmware update

After the driver has been installed, it is required to update the firmware. Note that this is needed only once, i.e. if you install the ESU1808 driver again later or if you install the hardware on a different Mac, you do not have to update the firmware. To start the process, launch the firmware updater:

The following window will appear:

Copyright © 1998-2026 ESI Audiotechnik GmbH - All rights reserved.

ESU1808: Readme

driver, control panel, firmware for Mac OS X

version: *2.0.2* | date: *2010-05-19* | filename: *ESU1808-Mac-v2_0_2.dmg* | product: *ESU1808*



Please check the version number of the *Current firmware* that is installed. If it is version is lower than 1.0.8, you need to click the *write firmware* button. If it is version number is 1.0.8 or even higher, please click *Exit* and you're done. The update to version 1.0.8 will take a few seconds. Once the update is complete, the following dialog will appear:



The message asks you to switch off or unplug the ESU1808. After you have done that, the following dialog will appear:



The message asks you to switch on or reconnect the ESU1808. After you have done that, the following dialog will appear:

Copyright © 1998-2026 ESI Audiotechnik GmbH - All rights reserved.



The message indicates that the update has been done successfully, both the *write firmware* and *Exit* button are grayed out. Please proceed by switch off or unplugging the USB cable on ESU1808 again. The dialog will change like this:



Please finish the firmware update program by clicking *Exit*. Then wait a few seconds and switch on or reconnect the ESU1808 again. Even though it is not really required, we strongly recommend you to reboot your system once before using ESU1808 in your audio applications.

Copyright © 1998-2026 ESI Audiotechnik GmbH - All rights reserved.